LUMISTAR

LS-25-P2 Multi-Band FM PCI Receiver **Data Sheet**

Description:

The Lumistar LS-25-P2 Multi-Band FM Receiver is the next generation tri-band, single-slot, fulllength PCI FM Receiver. The receiver is manufactured with one, two, or three frequency bands. This wideband designs supports PCM data rates up to 20 Mbps and includes an FM demodulated output for PCM data, two 70 MHz IF outputs, AM and linear AGC outputs. The design offers up to twelve 12 IF Bandwidths and twelve Video Filters. AC coupling with a low frequency filter is



employed to ensure a high quality data link with long strings of NRZ-L ones or zeroes. Down-converter versions of this design are available (LS-27-D Dual-Band Two Channel, the LS-27-D2 Multi-Band Downconverter or the LS-27-O

Quad-Band Single Channel) and can be used with the LS-32-R or LS-58-M for a single stream multi-mode solution or LS-33-P for a diversity combining solution (see separate data sheets). The 20 MHz Reference I/O allows the local oscillators of two down-converters to be locked together to achieve the high performance required in pre-detection diversity combining.

Key Features:

- Single, Dual, or Tri-Band Single Slot PCI Receiver with FM Demodulation
- AM, Controlled AGC, and Linear AGC Outputs
- **Supports Data Rates up to 20 Mbps**
- 8 dB Noise Figure (maximum); 6dB (typical)
- 70 MHz IF Outputs from Down-converter and 70MHz IF input to IF Receiver
- 20 MHz Reference I/O for use with the LS-33-P Pre-D Diversity Combiner
- Spectral and Eye Pattern Display Option using LS-22-SE PCI Board
- **Compatible with LDPS Software**

Frequency Band Options: Specify up to 3 bands from the table below

- 215-320 MHz P
- L 1435-1540 MHz
- U 1710-1850 MHz
- S 2200-2400 MHz
- E 2185-2485 MHz
- 70 MHz IF Input Ι
- K Custom

Lumistar, Inc. 2270 Camino Vida Roble, Suite L

PHONE: 760-431-2181

FAX: 760-431-2665

e-mail: sales@lumistar.net

Carlsbad, CA 92011

Tuner:

Input Bands Specify up to 3:

2185 – 2480 MHz (E-Band) 2200 – 2400 MHz (S-Band) 1710 – 1850 MHz (UL-Band) 1435 – 1540 MHz (L-Band) 215-320 MHz (P-Band) 70 MHz IF Input (no tuner) 4 or 12 depending on model

IF Bandwidths 4 or 12 depending on model 0.5, 1, 1.5, 2.5, 3.5, 4, 6, 8,

10, 12, 16, 20 MHz

Tuner Resolution 50 KHz Frequency Accuracy 0.002%

Noise Figure 8 dB (Maximum);

6 dB (Typical)

Operating Input Level -10 to threshold

Maximum Input Level +18 dBm without damage

Demodulator Outputs:

Demodulation Type FM and AM

Post-Detection BW 4 or 12 Software Selectable

Video Filters. Unless otherwise specified, they will be set for 50% of the IF

Bandwidths

Data Output Level Bi-Polar (with software

controlled output level to +/-3.5 Vp-p) with 75 Ohm

output impedance

AGC Output 0-4 V into $1\text{K}\Omega$, 0 V is -100

dBm, +4V is 0 dBm

AGC Time Constant 4 selectable time constants

1, 10, 100, 1000 ms

AGC Linearity +/- 2 dB into best fit straight

Line -15 dBm to threshold

+5 dB

AM Output 4 Vp-p into 10 K Ω

 $2.5 \text{ Vp-p into } 75\Omega$

AM Freq Response Selectable AM Low Pass

Filters: 50, 500, 5K, and 50

KHz

Additional Inputs/Outputs:

AGC Controlled -15 +/- 5 dBm signal into 50 Ohms

Linear 70 MHz IF 35 dB Gain (typ) into

50 Ohms. Max output

of +5 dBm

Bus Outputs:

Signal Strength and Peak Deviation

AM Modulation Depth

AM Frequency

Environmental:

Operating Temperature 0° to $+50^{\circ}$ C Non-Operating Temperature -25° to $+70^{\circ}$ C Operating Humidity 0 to 90% (Non-

condensing)

Non-Operating Humidity Protect from moisture and

contamination

Physical:

Current Required

Form Factor

IF Loop-back
Input Connections
Reference Connector
Input/Output Connector
D-Series to BNC/SMA cable

Full Size PCI Board
Software controlled
SMA for RF in
SMB for Ref I/O
D-Series 13W3
provided with

BNC for Baseband 1 Out BNC for Baseband 2 Out BNC for AM Out

BNC for AM Out BNC for AGC Out SMA for 70 MHz IF Out1

SMA for 70 MHz IF Out2 SMA for Linear IF Out 11 Watts Maximum 325 mA at +5V

530 mA at +12V 215 mA at -12V

Part Numbering: where X = Band

| LS-25-PA(X) | Single Band 4IF/4Video |
|---------------|--------------------------|
| LS-25-PB(X) | Single Band 12IF/12Video |
| LS-25-PA(XX) | Dual Band 4IF/4Video |
| LS-25-PB(XX) | Dual Band 12IF/12Video |
| LS-25-PA(XXX) | Tri Band 4IF/4Video |
| LS-25-PB(XXX) | Tri Band 12IF/12Video |