

Performance Starters

S10-P 4-65W SIN 220-240V BL 1000 APR

Range of Blue glow switch starters for igniting fluorescent lamps with electromagnetic ballast2-pin igniter in plastic (flame-retardant polycarbonate) canister and radio-interference suppression capacitor

Product data


| General Information | |
|-----------------------------|-----------|
| System Description | Single |
| | |
| Operating and Electrical | |
| Power (Nom) | 4-65 W |
| Pulse Voltage (Min) | 900 V |
| Non Reclosure Voltage (Min) | 140 V |
| Voltage (Nom) | 220-240 V |
| | |
| System characteristics | |
| Capacitor | Yes |
| | |
| Mechanical and Housing | |
| Housing Color | Blue |
| | |

| Cap-Base Information | 2 Pins |
|---------------------------------|--------------------------------------|
| | |
| Product Data | |
| Full product code | 871150069755428 |
| Order product name | S10-P 4-65W SIN 220-240V BL 1000 APR |
| EAN/UPC - Product | 8711500697554 |
| Order code | 928392110155 |
| Numerator - Quantity Per Pack | 1 |
| Numerator - Packs per outer box | 1000 |
| Material Nr. (12NC) | 928392110155 |
| Net Weight (Piece) | 7.000 g |

Datasheet, 2018, July 23 data subject to change

Performance Starters

Dimensional drawing



| Product | C (max) | E (max) |
|--------------------------------------|---------|---------|
| S10-P 4-65W SIN 220-240V BL 1000 APR | 40.3 mm | 21.5 mm |



© 2018 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. Philips and the Philips Shield Emblem are registered trademarks of Koninklijke Philips N.V.